



The first UL-924 LED Exit Sign Retrofit Kits approved for use with Edgelit and Sign Box styles.

Save Energy Save Money Reduce Waste

- UL-924 approved for use with Alkco, Cooper, High-Lites, Lightolier, Lithonia, Surelites, Big Beam and Western Lighting exit signs*
- **City of Chicago and New York approved**
- Eligible for various incentives including LEED points and Utility Rebates (ComEd and ConEd)
- Easy to Install: Splice into existing wires
- 10-year Limited Warranty#
- US Patent # 8,754,778
- Designed in Chicago, IL USA
- Lighting fixture extrusion made of recycled aluminum
- 89% Energy Saving/Approximately 1 year payback

See www.radionichitech.com for specific model numbers and warranty details

* \$ Energy Savings per Year

89% Energy Savings* - compared to conventional incandescent Exit Sign

*Based on a rate of \$0.12/KW

Incandescent Fixture	\$ 42.05
Fluorescent Fixture	\$ 18.92
ZXE-5000 LED	\$ 4.41

Energy Cost per Year/Fixture

ZXE-5000 Specifications:

Part #	LED Exit Sign Retrofit Kit Description:	Wattage
ZXE-5000-I-UNV	Internal Power Supply Universal Voltage 120-277 V All Mounting Hardware included. Length: 9"; 56 LEDs. Can be used in box-type or edgelit-type signs. Not intended for use with battery backup exit signs.	4.5 Watts
ZXE-5000-E-UNV	External (remote) Power Supply Universal Voltage 120-277 V All Mounting Hardware included. Length: 9"; 56 LEDs. Can be used in box type or edgelit-type signs. Not intended for use with battery backup exit signs.	4.5 Watts
ZXE-5000-I-BBUNV	Internal Power Supply for use with Battery Backup Exit Signs Universal Voltage 120-277 V All Mounting Hardware included. Length: 9"; 56 LEDs total; <i>Approved for use with the following battery backup exit signs: Cooper/Surelites CHX Series and Big Beam EFX Series</i>	4.5 Watts
ZXE-5000-E-BBUNV	External (remote) Power Supply for use with Battery Backup Exit Signs Universal Voltage 120-277 V All Mounting Hardware included. Length: 9"; 56 LEDs total; <i>Approved for use with the following battery backup exit signs: Cooper/Surelites CHX Series and Big Beam EFX Series</i>	4.5 Watts



46BS
US Patent #8,754,778



RADIONIC
HI-TECH, INC.

6625 W. Diversey Ave, Chicago, IL 60707 Phone (773) 804-0100 Sales@Radionic.net www.radionichitech.com